


Saving connections to more than one OM-SQ series data logger using the My Loggers feature of OMEGALOG®

My Loggers

The “My Loggers” feature allows you to add up to ten loggers to the Logger Selection. This is useful if you have a number of data loggers of the same or differing models with the same or differing communication settings.

Note: The Data Loggers should be connected to the PC and set up one after the other.


Connect the first data logger to PC and select type i.e. OM-SQ2010 Series.



From the OMEGALOG® Assistant select *Logger Control*.




And check that you are communicating with the data logger.



The example shows that the Logger Identification has the name *Desk 2010* (this has been set in Logger Set Up screen).

Close the logger control screen and in OMEGALOG® Assistant go to *Logger Selection* and *My Loggers, Add Logger*.



Type in the appropriate logger name and click the *OK* button.



Connect the second data logger to the PC.


From the OMEGALOG® Assistant select *Communication Wizard*.



Select the second type of communication required in this case USB and click the *Next* button.



Select the second USB device shown and click on the *Finish* button.




From the OMEGALOG[®] Assistant select *Logger Control*.




And check that you are communicating with the data logger.

The example shows that the Logger Identification has been set with the name *Workshop 2010*.



Close the logger control screen and in OMEGALOG® Assistant go to *Logger Selection* and *My Logger*, *Add Logger*.

Type in the appropriate logger name and click the *OK* button.



You will now be able to contact each of your loggers by going into *Logger Selection* and *My Loggers* and choosing a logger name you have setup.

