## Borescope with Detachable Screen for Wireless Viewing







## **Specifications**

Camera Image Rotation: Always 6p

Zoom: 4x

**Imaging Sensor: CMOS** 

**Total Pixels:** 

704 x 576 (PAL)/320 x 240 (NTSC)

Horizontal View Angle: 50°

Transmission Frequency: 2468 MHz

**Resolution:** 320 x 240 pixels (NTSC)/704 x 576 pixels (PAL) **Minimum Illumination:** 0 Lux

Modulation Type: FM Bandwidth: 18 MHz

Power Source: Li-ion

rechargeable batteries (included)

**Unobstructed Effective** 

**Transmission Range:** 10 m (32.8') **Waterproof Capacity:** IP67

(probe only)

**Dimensions:** 186 L x 145 W x 41 mm D (7.3 x 5.7 x 1.6") (excluding flexible tube)

**Weight (Approx.):** 530 g (19 oz)

**Monitor** 

Wireless: Up to 15.2 m (50') LCD Screen Type: 88.9 mm (3.5")

TFT-LCD

Effective Pixels: 320 (R.G.B.) x 240

Video System: PAL/NTSC

Transmission Frequency: 2414 MHz, 2432 MHz, 2450 MHz, 2468 MHz Exterior Supply Voltage: 5 Vdc

consumption current (maximum) 500 mA

Charge Time: 3 hours Work Time: 2 hours

Picture/Video Pixels: 320 x 240 Video Size: 27M byte/minute Frame Rate: 30 frame/second

Video Output Level:  $0.9\text{-}1.3 \text{ Vp-p } @75 \Omega$ 

**Receiving Sensitivity:** ≤ -85dBm **Dimensions:** 100 W x 70 D x 25 mm H

(4 x 2.8 x 1")


Weight (Approx.): 140 g (5 oz)
Operating Temperature: -10 to 50°C

(14 to 122°F)

**Operating Humidity:** 15 to 85% RH **Language:** English, Spanish, French,

Chinese, Portuguese

Data Logging: SD card (included)



To Order	
Model No.	Description
HHB400	88.9 mm (3.5") color LCD screen borescope

## Accessories

Model No.	Description
PE14	Borescope probe 1 m (3.3') electrically insulated
P230-1	Replacement probe 1 m (3.3') obedient metal
P230-1X	0.9 m (2.9') obedient metal extension

Comes complete with MicroSD memory card, extension tools: (mirror, magnet, pick-up hook), video interconnect cable, USB cable, AC adaptor, li-ion rechargeable batteries, blow mold case, and operator's manual.

Ordering Example: HHB400, 88.9 mm (3.5") color LCD screen borescope.