Timing Relays

TRFP240AC



- ✓ 20 Time Ranges and 10 Timing Functions
- ✓ Time Delays from 0.1 sec to 600 hrs
- Space-Saving, Compact Package
- ✓ High Repeat Accuracy of ±0.2%
- ✓ LED Indication
- 2 Form C DPDT Delayed Output Contacts
- ✓ 10 A Contact Rating

The TR Series Timing Relays are designed to meet most timing requirements by offering more flexibility in range of input voltage, timing range and functionality. Use a rotary switch to choose from 20 selectable time ranges from 0.1 second to 600 hours. We offer both a power triggered and signal triggered model—each with expanded operation modes. There is a green LED to indicate when power is ON and an orange LED when output is ON.

Specifications

Contact Configuration: 2 Form C, DPDT (delayed output)

Allowable Voltage/Current: 240 Vac, 30 Vdc/10 A

Max Permissible Operating
Frequency: 1800 cycles per hour

Rated Resistive Load: 10 A,

240 Vac/30 Vdc

Rated Inductive Load: 7 A,

240 Vac/30 Vdc

Horsepower Rating: ½ hp 120 Vac, ½ hp 240 Vac

Electrical Life: 500,000 operations

min (resistive)

Mechanical Life: 50,000,000

operations minimum

Operation System: Solid-state

CMOS circuit

Time Range: 0.1 sec to 600 hours Coil Rating: 100-240 Vac

Triggering: By signal



TRFP240AC shown larger than actual size.

RANGE

Pollution Degree: 2 (IE60664-1) **Overvoltage Category:** III

(IE60664-1)

Rated Operational Voltage: 100 to 240 Vac (50/60 Hz)

Voltage Tolerance: 85 to 264 Vac

(50/60 Hz)

Input OFF Voltage: Rated Voltage

x 10% minimum

Ambient Operating Temperature:

-20 to 65°C (-4 to 149°F)

Reset Time: 100 mS maximum Repeat Error: ±0.2%, ±20 mS Voltage Error: ±0.2%, ±20 mS Temperature Error: ±0.5%, ±20 mS

Setting Error: $\pm 10\%$ maximum Insulation Resistance: $100 \text{ M}\Omega$

minimum (500 Vdc)

Dielectric Strength Between Power and Output Terminals: 2000 Vac, 1 minute

Dielectric Strength Between Contacts of Different Poles: 2000

Vac, 1 minute

Dielectric Strength Between Contacts of Same Pole: 1000 Vac,

1 minute

Vibration Resistance: 10 to 55 Hz amplitude 0.5 mm; 2 hrs in each

of 3 axes

Shock Resistance: 10 G (operating extremes), 40 G (damage limits 3x in each of 3

ıxes)

Power Consumption (Approx): 6.5 VA @ 120 Vac/60 Hz, 11.6 VA

@ 240 Vac/60 Hz

Dimensions: 40 H x 36 W x 77.9

mm D (1.58 x 1.42 x 3.07")

Weight: 89 g (3 oz)

OPERATION

A: ON-Delay (Signal Start)

When a preset time has elapsed after the start input turned on while power is on, the NO output contact goes on

Item	Terminal No.	Operation			
Power	2-10				
Start	5-6				
Delayed	1-4, 8-11 (NC)				
Contact	1-3, 9-11 (NO)				
Indicator	PWR				
	OUT				
Set Time		l < → l l < → l Ta			


C: Cycle (Signal Start, ON First)

When the start input turns on while power is on the NO contact goes on. The output oscillates at a preset cycle (Duty Ratio 1:1).


Item	Terminal No.	Operation										
Power	2-10											
Start	5-6											
Delayed Contact	1-4, 8-11 (NC)											
	1-3, 9-11 (NO)											
Indicator	PWR											
	OUT											
Set Time			 T	Ť	⇔ T	⇔ T	Ť	⇔ T	Ť	⇔ T	Ta	←

E: Signal OFF-Delay

When power is turned on while the start input is on, the NO output contact goes on. When a preset time has elapsed after the start input turned off, the NO output contact goes off.




Note: T=Set Time, Ta=Shorter Than Set Time




B: Cycle (Signal Start, OFF First)

When the start input turns on while power is on, the output oscillates at a preset cycle (Duty Ratio 1:1), starting while the NO contact off.



D: Signal ON/OFF-Delay

When the start input turns on while power is on, the NO output contact goes on. When a preset time has elapsed while the start input remains on, the output contact goes off. When the start input turns off, the NO contact goes on again. When a preset time has elapsed after the start input turned off, the NO contact goes off



F: One-Shot (Signal Start)

When the start input turns on while power is on, the NO output contact goes on. When a preset time has elapsed, the output contact goes off.

•	,	•
Item	Terminal No.	Operation
Power	2-10	
Start	5-6	
Delayed	1-4, 8-11 (NC)	
Contact	1-3, 9-11 (NO)	
Indicator	PWR	
	OUT	
Set Time		T Ta

To Order			
Model No.	Description		
TRFP240AC	Timing relay, 100-240 Vac coil voltage, signal triggered		
D3PA3	11-pin octal socket		

Comes with installation guide.

Ordering Example: TRFP240AC, timing relay, with D3PA3 socket.