RTD Digital Controllers

4200A Series





- ✓ High-Accuracy to 0.1% of Span
- ✓ Single and Dual **Setpoint Models**
- ✓ 1.0° and 0.1° Models
- Adjustable Proportion Band
- Bright LED Display

The OMEGA® 4200A Series is an ideal controller for RTD applications. This quality-built linearized instrument is available in both 1.0° and 0.1° resolution models. Higher accuracies, accuracies 5 to 10 times greater than the typical 1% meter indicating controller, are achieved through a unique linearizing technique.

Specifications* **RTD Input**

Type: 100Ω platinum; alpha = 0.00385 (DIN curve) Configuration: 3 wires

External Lead Wire Resistance Effect: 0.1% span up to $10~\Omega$ per lead wire leg

Sensor Break Protection: Built-in, upscale on open sensor

Calibration Accuracy: 1.0° Resolution Model: ±0.1% of span ±1 digit 0.1° Resolution Model: ±0.2% of span ±1 digit

Stability: 0.1% for 30 to 130°F, 0.1%, 10% to 15% line voltage

Common Mode Rejection: Maximum error ±1°C with 240 V, 60 Hz applied as common mode signal between sensor

input and chassis ground

Series Mode Rejection: Maximum error ±1°C with series mode signal of 100 mV peak-to-peak @ 60 Hz

Control Output 1st Setpoint

(Adjustable Time Proportional):

Relay (Standard Model): SPDT relay 7 A resistive @ 120 Vac, 5 A

resistive at 240 Vac

Option "T" (Triac): Solid state plug-in triac rated 1 A holding and 10 A in-rush

Option "F" (Current Proportional): 4 to 20 mAdc into 1000 Ω maximum Option "DC" (DC Pulse): 20 Vdc

2nd Setpoint:

Relay (On/Off Only): SPDT. rated 3 A at 120 Vac

Adjustments

Proportional Band (Gain): 0 to 3% of span, or on/off; selectable Manual Reset (Offset): Adjustable Cycle Time: Automatically adjusts with

load requirement to give least wear with minimum ripple (10 s minimum)

Display and Indications

Temperature: Filtered LED, 3 or 3½ digits, 2 readings per second update; readability is 1.0° or 0.1° (°F or °C),

depending on model

Setpoint: By spring loaded switch, first or second setpoint is displayed in place of temperature; setpoint adjusted by 25 turn potentiometer; 1.0° or 0.1° setability

Outputs: LED indication for both first and second setpoints; LED are "on" when output drive signal present; "on/off" indication on relay and triac model; proportional

Temperature Overrange:

intensity for option "F" Red LED indication

Setpoint

Resolution: 1.0° or 0.1° (°F or °C),

depending on model

Repeatability: $\pm 0.1\%$ to $\pm 0.2\%$ of span Adjustment: By 25 turn potentiometer; see "setpoint" under "display

and indication" section. Power: 120/240 Vac (10%, -15%, 50/60 Hz); power consumption

less than 5 W



PR-10-2-100-1/4-12-E general-purpose RTD probe sold separately.

Environmental and Physical Operating Temperature: -1 to 54°C

(30 to 130°F) **Weight:** 1 kg (2 lb)

1/4 **DIN Case:** Metal; plug-in with screw terminal on rear; adjustable brackets for panel mounting; panel cutout is 92 x 92 mm (3.622 x 3.622")



OMEGACARESM extended warranty program is available for models shown on this page. Ask your sales representative for full details when placing an order. OMEGACARESM covers parts, labor and equivalent loaners.

Model Number	Sensor Type		Resolution	Accuracy ±1 Digit	No. of Setpoints
4201APF1 4201APC1	Platinum RTD $\alpha = 0.00385$ $\Omega/\Omega/^{\circ}$ C	0 to 999°F 0 to 600°C	1°F 1°C	±0.1% of Span	Single
4202APF1 4202APC1		0 to 999°F 0 to 600°C	1°F 1°C		Dual
4201APF2 4201APC2		-199.9 to 199.9°F -199.9 to 199.9°C	1°F 1°C	±0.2% of Span	Single
4202APF2 4202APC2		-199.9 to 199.9°F -199.9 to 199.9°C			Dual

Output Options (No Additional Cost)

Order Suffix	Option Type (First Output Only)		
-T	Triac		
-F	4 to 20 mA		
-DC	DC pulse		

Accessory

Model No.	Description
CNQUENCHARC	Noise suppression RC snubber (2 leads), 110 to 230 Vac

Comes complete with operator's manual.

Ordering Examples: 4202APF1, RTD digital controller.

OCW-3, OMEGACARESM extends standard 2-year warranty to a total of 5 years.

^{*} Specifications and configurations subject to change as advances in technology allow.